

ROWEN SP1 / SmartPRE

CONFIGURATION GUIDE

The following key combinations (symbol: ●) show the current setting when pressed briefly (<2sec) (LEDs on the right side).

To change a setting, press and hold and keys until the desired value is displayed. If pressed too long, the existing setting is retained.



KEY-COMBINATIONS

IN STAND-BY

General settings

ON ACTIVE SOURCE

Source-specific settings

CONFIGURATIONS

		Reset balance setting	Balance for source <i>neutral</i> 2-4db right 6-8db right 2-4db left 6-8db left
		Automatic power-off <i>never</i> <i>5min</i> <i>10min</i> <i>15min</i>	Automatic switch-on for source <i>off</i> <i>low</i> <i>medium</i> <i>high sensitivity</i>
		Permanent DAC <i>off</i> <i>on</i>	Fixed volume for source <i>off</i> <i>on</i>

LEARN IR REMOTE

After pressing the key combination (>2sec), press the button on the remote control twice to be learned.

		IR to switch-off	IR to select specific source
		IR for general volume -	IR for source and volume -
		IR for general volume +	IR for source and volume +

SERVICE

		Factory setting <i>reset</i>
--	--	---------------------------------